



Market Manual 7: System Operations

**Part 7.4: IESO-
Controlled Grid
Operating Policies**

Issue 17.1~~Issue 17.0~~

This document provides policy statements for reliable operation of the *IESO-Controlled grid*.

Disclaimer

The posting of documents on this Web site is done for the convenience of *market participants* and other interested visitors to the *IESO* Web site. Please be advised that, while the *IESO* attempts to have all posted documents conform to the original, changes can result from the original, including changes resulting from the programs used to format the documents for posting on the Web site as well as from the programs used by the viewer to download and read the documents. The *IESO* makes no representation or warranty, express or implied, that the documents on this Web site are exact reproductions of the original documents listed. In addition, the documents and information posted on this Web site are subject to change. The *IESO* may revise, withdraw or make final these materials at any time at its sole discretion without further notice. It is solely your responsibility to ensure that you are using up-to-date documents and information.

This document may contain a summary of a particular *market rule*. Where provided, the summary has been used because of the length of the *market rule* itself. The reader should be aware, however, that where a *market rule* is applicable, the obligation that needs to be met is as stated in the “Market Rules”. To the extent of any discrepancy or inconsistency between the provisions of a particular *market rule* and the summary, the provision of the *market rule* shall govern.

Document ID	IMP_POL_0002
Document Name	Part 7.4: IESO-Controlled Grid Operating Policies
Issue	Issue 17.0 Issue 17.1
Reason for Issue	Issue released for Baseline 16.0 1
Effective Date	September 13, 2006 December 6, 2006

Document Change History

Issue	Reason for Issue	Date
1.0	Unapproved version issued as part of Baseline 4.0	October 6, 2000
2.0	Unapproved version released for Baseline 6.0	February 26, 2001
3.0	Issue released for Baseline 6.2	May 22, 2001
4.0	Issue released for Baseline 6.4.	August 13, 2001
5.0	Issue released for Baseline 6.6	October 29, 2001
6.0	Issue released for Baseline 7.0	January 8, 2002
7.0	Issue released as update to Baseline 7.0	April 26, 2002
8.0	Update to Baseline 7.0	June 26, 2002
9.0	Issue release for Baseline 9.0	March 5, 2003
10.0	Issue released for Baseline 9.1	June 4, 2003
11.0	Issue released for Baseline 10.0	September 10, 2003
12.0	Issue released for Baseline 10.1	December 10, 2003
13.0	Issue released for Baseline 11.0	March 3, 2004
14.0	Issue released for Baseline 11.1	June 2, 2004
15.0	Issue released for Baseline 13.1	June 1, 2005
16.0	Issue released for Baseline 14.1	December 7, 2005
17.0	Issue released for Baseline 16.0	September 13, 2006
17.1	Draft Issue for Baseline 16.1	Decemeber 6, 2006

Related Documents

Document ID	Document Title

Table of Contents

Table of Contents	i
List of Figures	iii
List of Tables	iv
Table of Changes	v
Market Manuals	1
Market Policies	1
1. Introduction	3
1.1 Purpose.....	3
1.2 Scope.....	3
1.3 Overview	3
1.4 Roles and Responsibilities.....	4
1.5 Contact Information	4
2. Operating Authority	5
3. Communications	7
4. Reliability	9
4.1 High-Risk and Emergency Operating States	10
4.2 Operating Under Extreme Cold Temperatures.....	11
4.3 Voltage Control.....	12
4.4 Demand Control - Manual Load Shedding.....	12
4.5 Demand Control - Under Frequency Load Shedding (UFLS).....	13
4.6 Demand Control - Voltage Reductions	14
4.7 Special Protection Systems - In-Service at Market Launch.....	14
4.7.1 Governing Principles.....	14
4.7.2 Special Protection Systems Selection.....	15
4.7.3 Exclusion from L/R Selection	15
4.7.4 Restoration of Rejected Load.....	16
4.8 Special Protection Systems - Installed after Market Commencement	16
4.9 Network Configuration Change Requests.....	16
4.10 Automatic Reclosure Facility	17

4.11	Islanding.....	18
5.	Outage Management.....	19
5.1	Overall Policy.....	19
6.	Assessment of System Security and Adequacy	21
6.1	Overall Policy.....	21
6.2	Determination of Generation and Transmission Adequacy.....	21
6.3	Determination of System Security	23
6.4	Operating Reserve.....	24
6.5	Area Reserve for Load Security	25
7.	Compliance	27
Appendix A:	Forms	A-1
Appendix B:	Reliability Standards and Security Criteria.....	B-1
Appendix C:	SPS Restrictions During High Risk Operating State.....	C-1
Appendix D:	Load and Generation Rejection and Generation Runback Selection Criteria	D-1
Appendix E:	Emergency Operating State Control Actions	E-1
References	1

List of Figures

N/A

List of Tables

N/A

Table of Changes

Reference (Section and Paragraph)	Description of Change
<u>Appendix E</u>	<u>Clarified the IESO's policy with regard to curtailing Linked Wheel transactions.</u>
<u>Section 7</u>	<u>Corrected the reference to the Reliability Compliance Program.</u>

Market Manuals

The *market manuals* consolidate the market procedures and associated forms, standards, and policies that define certain elements relating to the operation of the *IESO-administered markets*. Market procedures provide more detailed descriptions of the requirements for various activities than is specified in the *Market Rules*. Where there is a discrepancy between the requirements in a document within a *market manual* and the "Market Rules" the "Market Rules" shall prevail. Standards and policies appended to, or referenced in, these procedures provide a supporting framework.

Market Policies

The "System Operations Manual" is Volume 7 of the *market manuals*, where this document forms "Part 7.4: IESO-Controlled Grid Operating Policies".

A list of the other component parts of the "System Operations Manual" is provided in "Part 7.0: "System Operations Overview", in Section 2, "About This Manual".

Conventions

The *market manual* standard conventions are as defined in the "Market Manual Overview" document.

– End of Section –

1. Introduction

1.1 Purpose

This document contains the *IESO* policies and standards for reliable operation of the *IESO-controlled grid*. These policies are intended to:

- provide guiding principles for the development of both internal and external operating procedures; and
- provide guidance to *IESO* operating staff when confronted with an operational situation that is not addressed in an operating procedure or a *market rules*.

This initial set of operating policies were taken from existing *IESO* and Ontario Hydro operating policy documents and revised where required to be consistent with: the new market structure *market rules*, obligations and authorities; and the applicable *NERC* reliability standards and *NPCC* criteria and guidelines. Revisions and additions to these policies will be made as required.

The introduction of competition in generation and supply of electricity and of customer choice has substantially replaced the traditional framework. To direct reliable operation of the *IESO-controlled grid*, including *security* and supply *adequacy*, the *IESO* will, to the extent practicable, use available market mechanisms. Where the *IESO* determines such mechanisms are unable to achieve reliable operation, it will take additional actions in accordance with the policies contained herein.

1.2 Scope

These policies apply to the *IESO* in its role to direct the reliable operation of the *IESO-controlled grid*.

These policies are in compliance with the applicable standards, policies and criteria established by *NERC* and *NPCC*, along with the “Electricity Act 1998” and the “Market Rules”.

1.3 Overview

Section 1 is an introduction, outlining the purpose and scope of the policies. The remaining sections detail policies in the following subject areas:

- Section 2 - Operating Authority
- Section 3 - Communications
- Section 4 - Reliability
- Section 5 - Outage Management
- Section 6 - Operation Planning

Appendix B details specific *reliability standards* and *security* criteria. Appendix C details restrictions on the use of *Special Protection Systems* during a *high-risk operating state*. Appendix D details criteria for selection of load and generation rejection and generation runback. Appendix E details the control actions the *IESO* will take when in anticipation of or upon declaration of an *emergency operating state*.

1.4 Roles and Responsibilities

The *IESO* is responsible for directing the operation and maintaining the *reliability* of the *IESO-controlled grid*.

It is the responsibility of *IESO* staff to adhere to these policies in their activities in directing the reliable operation of the *IESO-controlled grid*.

Maintenance of these policies is the responsibility of the *IESO*.

1.5 Contact Information

As part of the participant authorization and registration process, *applicants* are able to identify a range of contacts within their organization that address specific areas of market operations. The *IESO* will seek to contact these individuals for activities documented within this procedure, unless alternative arrangements have been established between the *IESO* and the *market participant*. If a *market participant* has not identified a specific contact, the *IESO* will seek to contact the Main Contact in PLC that is established during the participant authorization process, unless alternative arrangements have been established between the *IESO* and the *market participant*.

If the *market participant* wishes to contact the *IESO*, the *market participant* can contact *IESO* Customer Relations via email at <mailto:helpcentre@ieso.cacustomer.relations@ieso.ca> or via telephone, mail or courier to the numbers and addresses given on the *IESO*'s Web site (www.ieso.ca - or click on 'Have a question?' to go to the 'Contacting the *IESO*' page). If *IESO* Customer Relations is closed, telephone messages or emails may be left in relevant voice or electronic *IESO* mail boxes, which will be answered as soon as possible by Customer Relations staff.

– End of Section –

2. Operating Authority

The *IESO* is responsible for directing the operation and maintaining the *reliability* of the *IESO-controlled grid*. This responsibility is assigned to the *IESO* in the “Electricity Act, 1998” Section 5(c) and in the “Market Rules”, Chapter 5 Section 3.2, and is a condition of the *IESO License*. The *IESO* shall have the operating authorities necessary to meet this responsibility including the authority to direct reliable operation of the *IESO-controlled grid* as well as to monitor and enforce compliance with the applicable *reliability standards*.

Operating authorities of *IESO* and *market participant* shall be clearly established to facilitate secure and reliable operation of the *IESO-controlled grid*. *IESO* authorities shall recognize and respect the authority of *market participant* to take independent action to prevent damage to their equipment, to prevent safety hazards to their employees or the public or to prevent environmental damage.

The *IESO* authorities shall be consistent with *NERC* reliability standards and *NPCC* criteria and guidelines related to authorities and responsibilities for the *IESO* as *control area operator* and *security coordinator*.

The *IESO* shall exercise its operating authorities within the framework of *NERC* reliability standards and *NPCC* criteria and guidelines, *operating agreements*, *interconnection agreements*, *market rules* and other market documentation.

– End of Section –

3. Communications

Communication between the *IESO*, *market participant* and other entities (e.g. neighboring *control areas*) related to operation of the *IESO-controlled grid* must be consistent, efficient, and effective at all times i.e. when the *IESO-controlled grid* is in a *normal operating state*, a *high-risk operating state* or is in an *emergency operating state*. This is necessary so that the *IESO* can meet its legislated objects to direct the operations and maintain the *reliability* of the *IESO-controlled grid*.

To achieve this goal:

- The *IESO* shall facilitate and encourage open and prompt two-way communication between the *IESO* and *market participant*.
- *IESO* communication procedures shall comply with *NERC* reliability standards and *NPCC* criteria and guidelines related to communications.
- *IESO* communication procedures with *market participant* and others shall be consistent with the applicable *operating agreements*, *interconnection agreements*, *market rules* and other applicable market documentation.
- The *IESO* will, following contingencies or system events, communicate directly with the staff who exercise direct physical control of the affected *facility* and the respective authority center, in accordance with applicable agreements or procedures. This direct communication is essential so that the appropriate corrective action can be formulated and initiated promptly, based on first-hand information provided to the *IESO*.
- The *IESO* will have procedures that enable reliable operation of the *IESO-controlled grid* to be maintained during the loss of *IESO* telecommunication *facilities*.

– End of Section –

4. Reliability

The *IESO* will direct the operation of the *IESO-controlled grid* to meet all applicable *NERC* reliability standards and *NPCC* criteria and guidelines¹.

In directing the operation of the *IESO-controlled grid*, the *IESO* will adhere to the following principles:

- PREVENT System Disturbances resulting from contingencies that the *IESO-controlled grid* is required to withstand;
- CONTAIN System Disturbances to that portion of the *IESO-controlled grid* initially affected; and
- MINIMIZE the effect of System Disturbances on the reliable operation of the *IESO-controlled grid*, the *IESO-administered markets* and *market participants*.

The *IESO* will direct *market participants* to act/not act so as to maintain the *IESO-controlled grid* in a *normal operating state*. The *IESO* will also act or refrain from acting where doing otherwise is likely to lead to a *high-risk*² or *emergency*³ *operating state* (Chapter 5, Section's 2.4.2, 2.3.2, and 5.1.2.6 of the *market rules*).

For those areas where the *IESO* has determined that the consequences of *contingency events* will not have an adverse impact on the *interconnected system* in northeastern North America (i.e. non-*NPCC* impactive areas) (and *local areas*), the *IESO* will develop and *publish*, in consultation with *transmitters*, *market participants* and stakeholders, the appropriate operating criteria and standards. The *IESO* will direct operations in these areas in accordance with these operating criteria and standards.

For those areas where the *IESO* has determined that the consequences of *contingency events* will not have a significant adverse impact on the *reliability* of the *IESO-controlled grid* (i.e. "*local areas*"), the *IESO* will apply the same *reliability standards* and *security* criteria used before *market commencement date*.

For those circumstances/areas where the *IESO* has determined operation requires more stringent *reliability* criteria, the *IESO* will develop and *publish*, in consultation with *transmitters*, *market participant* and stakeholders, the appropriate operating criteria and standards. The *IESO* will, for

¹ *NPCC* Type "A" Documents (www.npcc.org); *NERC Reliability Standards* (www.nerc.com)

² *High Risk Operating State* definition:

"Market Rules": "when the observance of *security limits* under a *normal operating state* will expose the *integrated power system* to a significantly higher than normal probability of one or more *contingency events* and associated consequences, or of a condition that may lead to, but is not yet, an *emergency*." (Chapter 5 Section 2.4.1)

³ *Emergency Operating State* definition

"Market Rules": " when observance of *security limits* under a *normal operating state* will either: require *curtailment* of *non-dispatchable load*; or restrict transactions on *interconnected systems* during an *emergency* on the *IESO-controlled grid* or on a *neighbouring electricity system*." (Chapter 5 Section 2.3.1).

those circumstances/areas, direct operations in accordance with the more stringent operating criteria and standards.

The operation of those portions of the *IESO-controlled grid* where the consequences of *contingency events* can have a significant adverse impact on the *interconnected systems* in the MAPP Region are to be directed in accordance with the IESO- Manitoba and the IESO-Minnesota Power Interconnection Agreements.

The *IESO-controlled grid* is also connected to the East Central Area Reliability Council (ECAR), via tie-lines with Michigan. In general the *IESO* operates in accordance with *NPCC* criteria and Michigan operates in accordance with ECAR criteria. Concerning operation of the tie-lines between the *IESO-controlled grid* and Michigan, the most restrictive criteria will be used pursuant to the applicable agreement between the *IESO* and the appropriate Michigan authority.

4.1 High-Risk and Emergency Operating States

The *IESO* will direct the operation of the *IESO-controlled grid* under *high-risk* or *emergency operating states* in accordance with the *market rules*, applicable *NERC* reliability standards, *NPCC* criteria and guidelines, and *IESO* standards⁴ (Chapter 5, Section 5.8 and 5.9 of the *market rules*).

The conditions under which a *high-risk operating state* may be declared are included in “Market Manual 7: System Operations, Part 7.1: System Operation Procedures”.

In a *high-risk operating state* the *IESO* will temporarily and selectively increase the level of *IESO-controlled grid security* by application of High-Risk Security Limits. The *IESO* will also take additional actions as required in order to maintain an acceptable level of *IESO-controlled grid security*. This may include actions such as rejection, revocation or recall of equipment and *facility outages*. These additional actions will only be taken when necessary:

- to maintain the acceptable level of *security*; and
- to allow, after a recognized contingency, the *IESO* to be able to re-establish an acceptable level of *security* and re-prepare the *IESO-controlled grid* within the time permitted.

In a *high-risk operating state*, *security limit* violations are to be resolved and the *IESO-controlled grid* shall be re-prepared within 15 minutes rather than the 30 minute period that is permitted in a *normal operating state* (Chapter 5, Section 5.10.2.1 of the *market rules*).

Under internal and external (i.e. inside or outside the *IESO-controlled grid*) *high-risk* and *emergency operating states*, control actions by the *IESO* shall be structured in a manner which will first preserve system reliability and then restore normal operation of *IESO-administered markets* as soon as practicable (Chapter 5, Section 7.7.2 of the *market rules*). Also, the *IESO* will strive to achieve an acceptable level of *security*⁵ for the *IESO-controlled grid*, minimize the impact on the *IESO-administered markets*, while at the same time observing mutual protection and assistance provisions as contained in the applicable agreements between the *IESO* and other *security coordinators*.

⁴ *NPCC* Document A-03: Emergency Operation Criteria; *NERC Reliability Standards* - EOP series

⁵ The minimum acceptable level of *IESO-controlled grid security* is the level afforded by the observance of *emergency operating criteria*.

In an *emergency operating state*, all control actions including the shedding of *non-dispatchable load* should be taken to: (Chapter 5, Section's 2.3.3, 2.3.3A and 2.3.1.1 of the *market rules*)

- restore and maintain the level of *IESO-controlled grid security* afforded by observance of *emergency operating state security limits* (i.e. the minimum acceptable level) in:
 - those portions of the *IESO-controlled grid* where instability could jeopardize *interconnected systems*;
 - those portions of the *IESO-controlled grid* where instability and cascading *outages* will not affect *interconnected systems*, under High-Risk Conditions which are expected to last longer than 10 minutes;
- avoid damage to *market participant* equipment;
- respect environmental constraints; and
- maintain the integrity of the *interconnected systems*.

In anticipation of, or upon declaration of an *emergency operating state*, the *IESO* will take control actions as described in Appendix E.

4.2 Operating Under Extreme Cold Temperatures

In areas where historical trends show equipment problems during extreme cold temperatures, the *IESO* may implement control actions without the declaration of a *high-risk operating state*. If the *IESO* deems that a *high-risk operating state* is warranted, it will be declared in accordance with the *market rules*, applicable *NERC* reliability standards, *NPCC* criteria and guidelines, and *IESO* standards⁶ (Chapter 5, Sections 5.8 and 5.9 of the *market rules*).

The following are actions that put into effect a coordinated and consistent approach to maintain the *reliability* of the *IESO-controlled grid* during periods of extreme cold temperatures:

1. Should there be a forecast of abnormally cold temperatures on certain portions of the *IESO-controlled grid* where problematic trends have occurred, the *IESO* will enter into discussions with the applicable *transmitters* to formulate a plan to safeguard the *reliability* of the *IESO-controlled grid* by addressing concerns with equipment operation;
2. Considerations include but are not limited to:
 - *Adequacy*;
 - Recent historic pattern of equipment problems during extreme cold weather;
 - The extent to which the *transmitters* have taken measures to alleviate the risk;
 - Recent historic pattern of forced unavailability of transmission system equipment due to switching operation in the extreme cold;
 - Equipment performance during extended cold periods;
 - The need to have *transmitters'* maintenance and/or operations staff attend the site of the affected *facilities* or otherwise where priority dictates; and
 - The *IESO's* overall assessment of the risks.

⁶ *NPCC* Document A-03: Emergency Operation Criteria; *NERC Reliability Standards* - EOP series

3. Determine which sites are affected by the extreme cold. Apply actions on a site specific basis at stations that have demonstrated a recent historic pattern of equipment problems during cold weather.
4. Actions include but are not limited to:
 - Deferring routine work;
 - Rejecting and/or revoking any planned *outages* that may have an adverse impact on the *IESO-controlled grid* associated with stations that are expected to experience the extreme cold;
 - Recalling equipment on *outage* in cases when it can be reasonably expected that switching operations will not cause equipment failures during the extreme cold;
 - Issuing appropriate direction to *generators* and other *market participants* as required to enhance *adequacy*; and
 - Accommodating urgent *outage* requests to address equipment, environmental or safety concerns regardless of the temperature.
5. Affected *market participants* and *reliability coordinators* shall be advised as appropriate.

4.3 Voltage Control

The *IESO* will *dispatch*:

- generating unit reactive power within unit capability as specified in Appendix 4.2 of Chapter 4 of the "Market Rules";
- reactive control devices subject to *operating agreements*;
- reactive control devices subject to procurement contracts; and
- resources subject to *reliability must-run contracts*;

to maintain transmission line voltages within the ranges defined in Appendix 4.1 of Chapter 4 of the "Market Rules", as well as to respect operating *security limits* and equipment ratings.

The *IESO* will *dispatch*:

- reactive control resources subject to *operating agreements*; and
- generating unit reactive power within unit capability,

to meet *connected wholesale customer* or *distributor* voltage needs, so long as this action does not jeopardize the ability to maintain the transmission line voltages within the ranges defined in Appendix 4.1 of Chapter 4 of the "Market Rules".

4.4 Demand Control - Manual Load Shedding

When an *emergency operating state* has been declared and reduction in *demand* is required to safeguard the *security* of the *IESO-controlled grid*, the *IESO* will use the following principles in directing which *market participant* are to undertake manual load shedding to reduce *demand*: (Chapter 5, Section 10.1.1 of the *market rules*)

- Selection of the amount and location of load to be cut will be made on the basis of solving the operating problem and maintaining adequate *IESO-controlled grid security* levels.
- When time permits, load cuts via manual rotational load shedding schemes should be spread equitably across the *IESO-controlled grid* to the extent practicable so that an equitable distribution of the cuts is attained in terms of magnitude, duration, and frequency across the *IESO-controlled grid*.

4.5 Demand Control - Under Frequency Load Shedding (UFLS)

In specifying for each *distributor* and *connected wholesale customer*, in conjunction with the relevant *transmitter*, that is subject to automatic UFLS, the number, location, size and associated low frequency settings for the discrete blocks of load, the *IESO* policy is that: (Chapter 5, Section 10.4.6 of the *market rules*)

- (a) In all automatic UFLS areas, there must be at least 30% of area load connected to under-frequency relays, after accounting for relay *outages* and the impact of generators that may trip prematurely on under-frequency. By taking UFLS relay and feeder *outages* into account, in order to ensure at least 30% of load shedding is done, 35% of the total peak load of *connected wholesale customers* and *distributors* must be connected to UFLS relays. The discrete load shedding requirement is given in (b).
- (b) The UFLS relay connected loads shall be set to achieve the following: (Chapter 5, Section 10.4.7 of the *market rules*)
 - at 59.3 Hz, 12% of UFLS area load must be disconnected; and
 - at 58.8 Hz, an additional 23% of UFLS area load must be disconnected.
- (c) Any electrical area in Ontario that may become isolated from the rest of the *IESO-controlled grid* but remain connected to a neighboring system during a disturbance, must contain sufficient automatic UFLS capability so that the recovery of the neighboring system will not be prejudiced.
- (d) Inadvertent operation of a single under-frequency relay during the transient period following a System Disturbance should not lead to further system instability. For this reason, the maximum amount of load that can be connected to any under-frequency relay is 150 MW.
- (e) For purpose of UFLS, the province of Ontario is divided into five areas, i.e. Northwest, Northeast, West, East, and Central. The boundaries of those areas are given below.
 - (i) Northwestern area is bounded by Manitoba interconnection and west of East-West interface.
 - (ii) Northeastern area is bounded by east of East-West interface and north of North-South interface.
 - (iii) Western area is bounded by Michigan interconnection and west of BLIP interface.
 - (iv) Eastern area is bounded by New York interconnection at St Lawrence and east of Cherrywood and Bowmanville.
 - (v) Central area is Ontario excluding the areas given by (i), (ii), (iii) and (iv), i.e. area bounded by south of North-South interface, east of BLIP interface and west of Cherrywood and Bowmanville.

4.6 Demand Control - Voltage Reductions

The *IESO* may direct a *market participant* to initiate voltage reductions to preclude or mitigate *emergency operating states*, in accordance with the Emergency Control Action List. This would include precluding or mitigating: (Chapter 5, Section 10.1.1 of the *market rules*)

- (a) equipment thermal overloads;
- (b) insufficient *generation capacity* to satisfy non-dispatchable *demand*;
- (c) violations of high-risk or *emergency* limits; or
- (d) *Operating Reserve* shortfalls.

4.7 Special Protection Systems - In-Service at Market Launch

4.7.1 Governing Principles

The *IESO* will direct the operation of *Special Protection Systems (SPSs)* that are in-service at *market commencement date* in accordance with the applicable *reliability standards*⁷ to: (Chapter 5, Section 8.1.2 of the *market rules*)

- (e) increase the capability of power transfers across the *IESO-controlled grid* while providing normal *security* levels; or
- (f) provide additional *IESO-controlled grid security* beyond that required for normal criteria contingencies.

The overriding concern in the application of an *SPS* is its potential impact on *IESO-controlled grid security* following the malfunction of an *SPS*, i.e. the failure of an *SPS* to operate when required, or the inadvertent operation of an *SPS*. All *SPSs* must therefore be classified as Type I, II or III⁸ as specified in the *NPCC* criteria⁹, so as to pre-determine the potential impact of a malfunction. The *IESO-controlled grid* does not currently have any Type II *SPSs* installed.

The determination of the impacts of *SPS* malfunction are carried out at theoretical study limits (i.e. without operating limit margin applied).

Type I *Special Protection Systems* may only be utilized when adequate *facilities* for achieving an acceptable level of reliable operation are unavailable for service, unless specific *NPCC* approval to utilize the *SPS* otherwise has been obtained.

Type II or Type III *Special Protection Systems* may be utilized when required, without the above constraints.

⁷ *NPCC* Document B-11: *Special Protection System Guidelines*, March 1999

⁸ Definitions of Type I, II and III *SPSs* contained in "Market Manual 7: System Operations, Part 7.6: Glossary of Standard Operating Terms"

⁹ *NPCC* Document B-11 *Special Protection System Guideline*

When employed, *SPSs* must be utilized in a manner, which will: (Chapter 5, Section 8.2.2A of the *market rules*)

- (g) Maintain an adequate level of *IESO-controlled grid security* while satisfying obligations to interconnected power systems.
- (h) Ensure manageable system operation and compatibility with existing policies, strategies and procedures.
- (i) Minimize the impact of load rejection (L/R) on the community, by distributing interruptions of prolonged duration amongst customers and satisfying *local area reliability* performance standards.

When employing an *SPS* to increase the capability of power transfers across the *IESO-controlled grid*, consideration should be given to the risks associated with possible equipment damage and customer load interruption. This assessment should be made with due regard to the probability of the occurrence of the contingency that would initiate the operation of the *SPS* and the anticipated exposure period.

4.7.2 Special Protection Systems Selection

An *SPS* should be selected as required, such that following its operation, operator action can be taken to restore *IESO-controlled grid security* consistent with these policies.

The use of an *SPS* during periods when there is an increased probability of the occurrence of the initiating condition that would operate the *SPS*, i.e. when the *IESO-controlled grid* is in *high-risk operating state*, is subject to the restrictions contained in Appendix C.

SPS selection restrictions related specifically to High Risk Conditions are considered to be High-Risk Security Limits.

An *SPS* may be used selectively to provide additional *security* beyond criteria applicable under a *normal operating state* (i.e. to respect contingencies beyond those normally recognized), in accordance with *the following criteria*.

- (j) The additional selective use of an *SPS* in this regard must be such that it does not conflict with any arming restrictions associated with respecting criteria applicable under a *normal operating state*, specifically those associated with High Risk Conditions.
- (k) Thus, an *SPS* can only be utilized to respect specific contingencies beyond those normally recognized, provided the required degree of contingency selection selectivity is available.

Specific criteria for selection of load rejection, generation rejection (G/R) and generation runbacks are included in Appendix D.

4.7.3 Exclusion from L/R Selection

The purpose of recognizing excluding loads from L/R selection is to minimize the impact of L/R on the community and, at the same time, maintain a L/R scheme which is operationally manageable and secure.

Loads will be considered for exclusion from the L/R selection in recognition of the following:

- (l) cause public safety hazard,
- (m) result in environmental hazards;
- (n) planned or forced outages equipment directly associated with L/R tripping or restoration;
- (o) planned or forced outages equipment which may degrade the integrity of L/R tripping or restoration, such as but not limited to: relaying, station supervisory control equipment; or
- (p) load transfer which result in normally excluded load is required to be supplied from a source connected to the L/R scheme.

The market participant request exclusion shall submit the request to the *IESO* in accordance with the “Part 7.3: Outage Management”.

4.7.4 Restoration of Rejected Load

The restoration of rejected load shall be under the direction of the *IESO* shift operator. In the event the rejected load can not be restored within 30 minutes, other relevant load may be substituted.

4.8 Special Protection Systems - Installed after Market Commencement

The market participant will register any new or modified *SPS* in accordance with the “Part 1.2: Facility Registration, Maintenance and Exit”.

The IESO will use *NPCC* criteria and guidelines in its assessment of any new or modified *SPS*- obtain appropriate approvals from *NPCC*.

The market participant will notify the *IESO* prior to placing in-service any new or modified *SPS* in accordance with the “Part 7.3: Outage Management”.

The IESO will direct the operation of any new *SPS* in accordance with applicable *reliability standards* as outlined in Sections 4.6.1 and 4.6.2.

4.9 Network Configuration Change Requests

A transmitter may propose control action and/or changes to network configurations on the *IESO-controlled grid* to maintain continuity of transmission path to individual customers connected to the *IESO-controlled grid* and/or manage individual *delivery point* performance. The *transmitter* proposals may include changing normal *IESO-controlled grid* open points, transferring loads to alternate supplies, etc. The *IESO* shall review and approve a proposed network configuration request unless the resulting configuration either: (Chapter 5, Section 3.2.1 of the *market rules*)

- (q) degrades the *reliability* of the *IESO-controlled grid*;
- (r) results in change(s) to operating *security limits*/transfer capability;
- (s) results in inconsistent application of established *security* criteria and *reliability standards*;

- (t) imposes additional exposure to loss of essential *station service* supply to Nuclear Generating stations;
- (u) exposes the *IESO-controlled grid* to additional contingencies;
- (v) imposes additional risk/restrictions related to post-contingency *response* to recognized contingencies; or
- (w) results in changes in generation *dispatch* and/or could result in a change in market clearing price and/or result in constrained on or off payments to another *market participant*.

The above principles are applicable during normal operation including *planned outages*. It is expected that *transmitter* proposals for specific situations will be identified and approved in advance as part of limitations and/or operating restrictions. The *IESO* will include such pre-approved proposals in its instructions for directing the operation of the *IESO-controlled grid*.

During abnormal situations i.e. *forced outages*, responding to contingencies, system restorations, unacceptable risk to customer etc. the *IESO* may deviate from the above principles while respecting the intent to the extent possible.

4.10 Automatic Reclosure Facility

The *IESO* will use *NPCC* criteria and guidelines¹⁰ in its assessment of automatic reclosure *facilities* on the *IESO-controlled grid* which are employed to provide quick restoration of a circuit following tripping due to transient faults. The *IESO* policy is as follows: (Chapter 5, Section 3.2.2 of the *market rules*)

- Automatic reclosure settings shall be based on *market participant* equipment impact and *market participant* supply continuity.
- A faulted circuit is automatically re-energized from a single preferred breaker with undervoltage supervision and a minimum time delay of 5 seconds. In areas where studies indicates that higher speed reclosure has no impact on the *security* of the *IESO-controlled grid*, reclosing with a time delay of less than 5 seconds may be considered.
- The circuit should be automatically re-energized at the end remote from a generating station to avoid or reduce any shock loading of the generating units in the event of an unsuccessful reclosure. The breaker chosen for the re-energization of the circuit should be the one that would result in the least disruption in the event of a breaker failure upon an unsuccessful reclosure.
- The remaining breakers should be automatically reclosed with synchrocheck supervision, unless there is no electrically close generating station, then voltage presence supervision with a nominal time delay of 0.5 seconds may be used. For reclosing at thermal *generator* stations, the synchrocheck angle selection should not allow reclosures which result in the instantaneous power changes on any *generator* exceeding 0.5 per unit of its MVA rating.
- Automatic reclosure shall not be used to re-synchronize a generating unit that has separated from the *transmission system*.

¹⁰ *NPCC* Document B-1: Guide for the Application of Autoreclosing to the Bulk Power System.

- Operating *security limits* are derived such that the system must successfully withstand an unsuccessful automatic reclosure (open-close-open sequence) operation.

4.11 Islanding

- (x) Where a single contingency can create an island and where voltage or frequency cannot be monitored and controlled, *IESO* policy shall be to take pre-contingency control actions, such as arming of a *SPS*, or configuration change to collapse the under-generated island. For local areas, the *IESO* will not commit additional generation pre-contingency to allow a post-contingency island to survive (Chapter 5, Section's 3.2.1 and 5.1.2.1 of the *market rules*).
- (y) Where a single contingency results in an over-generated island and where voltage or frequency can be monitored and controlled, *IESO* will allow the island to operate provided:
- that the island is restricted to a well-defined part of the *IESO-controlled grid*, and
 - *IESO* studies show that voltage and frequency can be controlled to within acceptable steady state values.

When available, *SPSs* may be used to ensure that an over-generation island will continue to operate following an contingency.

- (z) For areas where the consequences of a contingency cannot be shown to be restricted to a well-defined part of the *IESO-controlled grid*, the *IESO* will take pre-contingency actions to avoid, where possible, a single contingency resulting in an island, and will constrain units on to ensure an over-generated island.
- (aa) For those areas where there are specific practices in place to deal with potential islanding, these practices will be documented and must be followed.

– End of Section –

5. Outage Management

5.1 Overall Policy

In its role to review, assess, approve, reject, revoke and recall proposed *outages* of *market participant registered facilities* and associated equipment, the *IESO* objective is to maintain reliable operation of the *IESO-controlled grid*. In its review, assessment, approval, rejection, revocation and recall of *outages*, the *IESO* will comply with the applicable *market rules*. The *IESO* will reject, revoke or recall an *outage* if required to maintain reliable operation of the *IESO-controlled grid*, including overall *adequacy* of the *IESO-controlled grid* (Chapter 5, Section 6.2 - 6.4B of the *market rules*).

The *IESO* will deal fairly and appropriately with *market participant* and comply with the applicable *market rules* and procedures. The *IESO* will provide timely information that is accurate to the best of its knowledge to *market participant* so as to facilitate *market participant* co-ordination of *outages* and the market mechanisms to resolve *outage* conflicts.

The *IESO* will work with neighboring utilities, transmission asset owners and *control areas* to influence, to the extent possible, *outages* of *facilities* and equipment outside of the *IESO-controlled grid*, whose *outage* would impact the reliable operation of the *IESO-controlled grid*.

- End of Section -

6. Assessment of System Security and Adequacy

6.1 Overall Policy

The *IESO* will develop, maintain and implement plans for the reliable operation of the *IESO-controlled grid* to meet all applicable *NERC* reliability standards and *NPCC* criteria and guidelines¹¹.

The *IESO* will develop and *publish* load forecasts, *security* and *adequacy* assessments, pre-dispatch and *real-time schedules* to meet all applicable *market rules*¹² and procedures¹³.

6.2 Determination of Generation and Transmission Adequacy

When assessing generation and transmission *adequacy*, the *IESO* will consider the following factors: (Chapter 5, Section 7.1.1 of the *market rules*)

- (bb) forecast primary *demand* (non-dispatchable + losses) and *dispatchable load*;
- (cc) load forecast uncertainty;
- (dd) additional contingency allowance;
- (ee) forecast generation availability, capacity and *energy* capability, including the available but not operating (ABNO) units and generation external to Ontario and tie-line capability from outside the *IESO-controlled grid*
- (ff) forecast transmission *facility* capability, planned availability and *forced outages*;
- (gg) applicable operating *security limits*; and
- (hh) acceptable voltage ranges.

When assessing generation *adequacy*, the *IESO* will compare forecasted *demand* to available resource capacity and *energy*, including available generation external to Ontario. For the purposes of identifying potential *adequacy* problems and/or exigencies potentially impacting on the coordination of *outages* that could give rise to shortfalls in *generation capacity*, the *IESO* will use the following criteria for *normal operating states*:

¹¹ *NERC Reliability Standards - TOP-002, EOP-001, EOP-003, EOP-005 and EOP-008*;
NPCC Documents: A-2 - Basic Criteria for Design and Operation of Interconnected Power Systems; B-8 - Guidelines for Area Review of Resource Adequacy

¹² “Market Rules” Chapters 5 and 7

¹³ “Market Manual 2: Market Administration, Part 2.8: Providing 10-Year Forecast and Assessment Information Requirements and Report”

- (ii) For the *dispatch day* and two days following the *dispatch day* daily assessment, an acceptable level of *adequacy* is achieved if
- available resources, based on installed capacity, estimated imports and *outage* information, exceed forecasted primary *demand* by at least the *Operating Reserve* requirement, and
 - available resources, based on *energy* production of *energy*-limited resources, installed capacity of non-*energy*-limited resources, estimated imports and *outage* information, exceed forecasted primary *demand* in MWh.

In the event that *IESO* determines that there is not an acceptable level of resources in the short-term, the *IESO* will take necessary actions such as:

- publishing information necessary to allow the market to react to *adequacy* concerns;
- activating *reliability must-run contracts* to address *local area adequacy* only (i.e. not permitted to address lack of overall system generation *adequacy*);
- *outage* rejection, revocation, recall; and
- issuing system advisory notices with the expected actions to be taken (e.g. voltage reductions, public appeals, load shedding).

- (jj) For the balance of daily assessment up to 14 days following the *dispatch day*,
- during the months between March and November, inclusive, an acceptable level of *adequacy* is achieved if forecast available resources, based on installed capacity and *outage* information, exceed forecasted primary *demand* by the *Operating Reserve* requirement plus the next largest half-contingency plus load forecast uncertainty.
 - during the months of December, January and February, inclusive, an acceptable level of *adequacy* is achieved if forecast available resources, based on installed capacity and *outage* information, exceed forecasted primary *demand* by the *Operating Reserve* requirement plus the next largest contingency plus load forecast uncertainty.
- (kk) For the weekly assessment from day 15 following *dispatch day* out to the end of week 4 following the *dispatch week*,
- during the months between March and November, an acceptable level of *adequacy* is achieved if
 - Forecast available resources, based on installed capacity and *outage* information, exceed forecasted primary *demand* by the linear interpolation between the *Operating Reserve* requirement plus the next largest half contingency plus load forecast uncertainty and an amount such that the Loss of Load Expectation (LOLE) is less than 0.1 days per year, consistent with *NPCC* requirements¹⁴; and
 - Available resources, based on *energy* production of *energy*-limited resources, installed capacity of non-*energy*-limited resources, estimated imports and *outage* information, exceed forecasted primary *demand* in MWh.
 - During the months of December, January and February, an acceptable level of *adequacy* is achieved if forecast available resources, based on installed capacity and *outage* information, exceed forecasted non-dispatchable *demand* by an amount such

¹⁴ *NPCC* Document A-2: Basic Criteria for Design and Operation of Interconnected Power Systems

that the Loss of Load Expectation (LOLE) is less than 0.1 days per year, consistent with NPCC requirements.¹⁵

- (II) For the 18 month and 10 year assessments an acceptable level of *adequacy* is achieved if forecast available resources exceed forecasted *demand* by an amount such that the Loss of Load Expectation (LOLE) is less than 0.1 days per year, consistent with NPCC requirements.¹⁶

When assessing transmission *adequacy*, the IESO will compare forecast transmission flows with the applicable operating *security limits* under a range of load conditions and *generator* and transmission *facility* availability conditions. Transmission is considered adequate if forecast loads can be supplied without exceeding the applicable operating *security limits*, and acceptable system voltages can be maintained.

6.3 Determination of System Security

The IESO will maintain IESO-controlled grid security such that satisfactory post-contingency performance will be experienced following recognized contingencies of specified severity as described in Appendix B.

The IESO will take all necessary steps including the interruption of *non-dispatchable load*, except in non-NPCC impactive areas during normal system conditions, to restore the operation of the IESO-controlled grid to an *emergency operating state* respecting corresponding limits within the target restoration times specified in "Market Rules" Chapter 5, Section 5.10.2.1. The criteria for deriving the *emergency operating state* limits are described in Appendix B. The following summarizes the criteria and actions used to maintain *security* throughout the IESO-controlled grid and to avoid or minimize shedding of *non-dispatchable load*.

Criteria	Action	NPCC Impactive Area	NON-NPCC Impactive Area	
			Normal System Condition	High Risk System Condition
Respect NPCC Criteria as per Appendix B	using all available control actions ¹ including the shedding of <i>non-dispatchable load</i>	X		
Respect Non-NPCC Impactive Criteria as per Appendix B	using all available control actions ¹ including the shedding of <i>non-dispatchable load</i>		X	X ²

¹⁵ NPCC Document A-2: Basic Criteria for Design and Operation of Interconnected Power Systems

¹⁶ NPCC Document A-2: Basic Criteria for Design and Operation of Interconnected Power Systems

Criteria	Action	NPCC Impactive Area	NON-NPCC Impactive Area	
			Normal System Condition	High Risk System Condition
Restore security of the <i>IESO-controlled grid</i> to respect <i>emergency</i> condition limits following a recognized contingency	using all available control actions ¹ including the shedding of <i>non-dispatchable load</i> post-contingency	X		X
Restore security of the <i>IESO-controlled grid</i> to respect <i>emergency</i> condition limits following a recognized contingency	using all available control actions ¹ without shedding of <i>non-dispatchable load</i> post-contingency		X	

Notes:

- To avoid or to minimize *non-dispatchable load* shedding, in addition to the *emergency operating state* control actions listed in Appendix E, the following control actions may be used where appropriate:

Load transfers;

Network configuration change, only if it does not contribute to additional risks to *generator* or load;

Phase shifter adjustment;

Appendix E details the *emergency operating state* control actions.

- If limits are available; in general limits are not available for the Non-NPCC Impactive area during high-risk condition.

6.4 Operating Reserve

The purpose of *Operating Reserve* is to ensure there is adequate generation to match the load in order to: (Chapter 5, Section 4.5.1 of the *market rules*)

- (mm) cover or offset unanticipated increases in load during a *dispatch day* or *dispatch hour*;
- (nn) replace or offset capacity lost due to the *forced outage* of generation or transmission equipment; or
- (oo) cover uncertainty associated with the performance of *generation facilities* or *dispatchable loads* in responding to the *IESO's dispatch instructions*.

The 60 Hz and 25 Hz systems are considered as a single system for determination of *Operating Reserve* with spare capability on the interconnecting frequency changers serving as the means for transferring this capability from one system to the other (Chapter 5, Section 4.5.5 of the *market rules*).

Operating Reserve shall be distributed so as to ensure that it can be utilized for any contingency resulting in generation loss without exceeding equipment or *transmission system* limitations and so that the requirements of "Area Reserve" in Section 6.5 are met.

Operating reserve requirements will be defined in accordance with the policies of the relevant *standards authorities*¹⁷.

Voltage Reductions will only be included in *Operating Reserve* when the market mechanisms to provide *Operating Reserve* do not provide an adequate amount of *Operating Reserve*.

6.5 Area Reserve for Load Security

The *IESO* will schedule area reserve using available means including market mechanisms such as requesting *offers* from *generators* and *bids* from *dispatchable load* to avoid shedding *non-dispatchable load* and to respect operating *security limits* following permanent loss of single elements of generation or transmission (Chapter 5, Section 4.5.5 of the *market rules*).

During abnormal conditions on the *IESO-controlled grid*, the *IESO* may schedule area reserve that results in carrying total reserve more than the normal required *Operating Reserve*. The *IESO* may also take additional control action to maintain area reserve (e.g., under high-risk operating state).

In some portion of the system, installed *facilities* may not meet design requirements or supply *reliability* may deviate significantly from standard. These will require individual assessment in situations where market mechanisms do not meet Area reserve requirements, in addition to the *emergency operating state* control actions listed in Appendix E, the following measures should be included as area reserve where appropriate to avoid or to minimize *non-dispatchable load* shedding:

1. Load transfers;
2. Network configuration change, only if it does not contribute to additional risks to the generator or load;
3. Phase-shifter adjustment.

- End of Section -

¹⁷ NPCC Criteria Document A-06; NERC Reliability Standards – BAL-002

7. Compliance

The *IESO* Reliability Compliance Program (IRCP) shall be the means by which the *IESO* aligns with and assures that the *reliability* requirements of the *standards authorities* compliance programs are met. “Part [2.47.9](#): Reliability Compliance Program” specifies the procedural requirements for the program.

The IRCP is designed to cover *market participant* reporting requirements and to require those entities responsible to ensure that the obligations to the *standards authority* are attained.

This will require *market participants* to perform specific functions in terms of operations, maintenance, testing and certification of compliance on an annual basis.

- End of Section -

Appendix A: Forms

There are no forms used in this document.

– End of Section –

Appendix B: Reliability Standards and Security Criteria

Refer to *NPCC "A"* documents

Refer to Appendix 4.1 of Chapter 4 of the *Market Rules* for performance standards related to the *transmission system*:

- frequency variations; and
- voltage variations.

B.1 SATISFACTORY POST-CONTINGENCY PERFORMANCE

The *IESO-controlled grid* must display satisfactory performance following a fault:

- (pp) The *IESO-controlled grid* must be stable with all unfaulted elements remaining in service except those associated with normal fault clearance and Special Protection Schemes if employed.
- (qq) The post-contingency steady-state loading of all *IESO-controlled grid* elements must be within their ratings as provided by the *facility* owners.
- (rr) The *IESO-controlled grid* must be able to withstand manual energization of the faulted element without prior readjustment of generation levels unless specific instructions to the contrary are provided. Such instructions will be embodied in Operating Security Limits and will normally apply only under specified conditions of loading in instances where post-contingency conditions would present a radical departure from the normal system configuration.

The post-contingency voltage levels must be within the limits as specified in B.3.2.

B.2 RECOGNIZED CONTINGENCIES

The operating security limits shall be based on the following criteria:

B.2.1 NPCC IMPACTIVE AREAS

Those portions of the *IESO-controlled grid* where the consequences of an *NPCC* normal criteria contingency could have a significant adverse impact on the *interconnected systems* in northeastern North America are to be operated so that satisfactory transient performance and acceptable post-contingency steady-state conditions will be experienced following the most severe of the contingencies listed below with due regard to reclosing *facilities*.

- a. When the *IESO-controlled grid* is in *normal operating state*, operating *security limits* will be based on the following recognized contingencies
 - (i) A permanent three-phase fault on any *generator*, transmission circuit, transformer or bus section with normal fault clearing.
 - (ii) Simultaneous permanent phase to ground faults on the same or different phases of each of two adjacent transmission circuits on a multiple transmission circuit tower, with normal fault clearing. If multiple circuit towers are used only for station entrance and exit purposes, and if they do not exceed five towers at each station, this condition is an acceptable risk and is excluded.
 - (iii) A permanent phase to ground fault on any *generator*, transmission circuit, transformer, or bus section, with delayed fault clearing.
 - (iv) Loss of any element without a fault.
 - (v) A permanent phase to ground fault on a circuit breaker, with normal fault clearing.
 - (vi) Simultaneous permanent loss of both poles of a direct current bipolar *facility*.
 - (vii) The failure of a circuit breaker associated with a Special Protection Scheme to operate when required following: loss of any element without a fault; or a permanent phase to ground fault, with normal fault clearing, on any transmission circuit, transformer or bus section.
- b. When the *IESO-controlled grid* is in an *emergency operating state*, operating *security limits* based on the following contingencies will apply:
 - (i) A permanent three-phase fault on any *generator*, transmission circuit, transformer, or bus section, with normal fault clearing.
 - (ii) Loss of any element without a fault.
- c. When the *IESO-controlled grid* is in a high-risk operating state, operating *security limits* will be developed in order to avoid or to minimize the frequency or occurrence of specific consequences arising from design criteria contingencies, or to respect contingencies beyond design criteria (High-Risk Security Limits). In general, the development and application of High-Risk Security Limits to avoid or to minimize the frequency of occurrence of specific consequences are considered when the observance of Normal Operating State Security Limits includes:
 - (i) The use of generation rejection or automatic load rejection for a single element contingency.
 - (ii) The use of a significant amount of generation rejection or automatic load rejection for a double element contingency.

In specific cases, High-Risk Security Limits may be used to provide a *security level* temporarily higher than design standard (e.g. loss of two circuits versus loss of one circuit) based upon operating experience.

B.2.2 NON-NPCC IMPACTIVE AREAS

For those areas where the *IESO* has determined that the consequences of the contingencies specified in a) above will not have an adverse impact on the *interconnected systems* in northeastern North

America (i.e. " non-*NPCC* impactive areas"), the *IESO* will use the following *reliability standards* and *security* criteria:

- d. Only single contingencies are recognized:
 - (i) the loss of an element without a fault, and
 - (ii) a phase-to-phase to ground fault on any *generator*, transmission circuit, transformer or bus section with normal fault clearing.
- e. With all elements in service, a recognized contingency shall not result in load loss except where such load is directly connected to the faulted element or the load is intentionally interrupted via the operation of a Load Rejection *SPS* operation.
- f. With one element out of service, a recognized contingency may result in load loss by configuration only or as the result of Load Rejection *SPS* operation.
- g. Under multiple *outage* conditions where instability or overloads will have an adverse impact on the *interconnected systems* in northeastern North America, the criteria in section B.2.1 above must be applied.

In some portion of the system, installed *facilities* may not meet design requirements or supply *reliability* may deviate significantly from standard. These area will require individual assessment.

B.2.3 LOCAL AREAS

For those areas where the *IESO* has determined that the consequences of the contingencies specified in a) above will not have a significant adverse impact on the *reliability* of the *IESO-controlled grid* ("*local areas*"), the *IESO* will apply the same *reliability standards* and *security* criteria used before *market commencement date*. The *reliability standards* and *security* criteria used before *market commencement date* will be documented and must be followed. The *reliability* of *local areas* will be reviewed jointly between the *IESO* and *transmitters* at least once annually.

B.2.4 MAPP IMPACTIVE AREAS

For those portions of the *IESO-controlled grid* where the consequences of contingencies specified in a) above can have a significant adverse impact on the *interconnected systems* in the MAPP Region, a jointly agreed upon criteria between the *IESO* and neighboring utilities (i.e. Manitoba Hydro and Minnesota Power) will continue to be observed until adequate facilities are in service.

B.3 CRITERIA FOR DERIVATION OF OPERATING SECURITY LIMITS

This section sets forth the criteria to be used by the *IESO* in analyzing the results of off-line computer studies conducted to establish Operating Security Limits.

The *IESO-controlled grid* is to be operated so that satisfactory pre-contingency steady-state conditions are maintained. Transient stability of the *IESO-controlled grid* will be maintained and acceptable post-contingency steady-state conditions will be experienced following the occurrence of the most severe contingency for which the *IESO-controlled grid* is designed.

Satisfactory transient stability and pre and post-contingency steady-state behavior may be considered is assured if the Operating Security Limits are based upon the criteria stated herein.

B.3.1 PRE-CONTINGENCY CRITERIA

In deriving Operating Security Limits for Normal Conditions and for Emergency Conditions, the *IESO-controlled grid* must meet the criteria listed below in the steady state prior to contingency simulation.

Steady-State Stability

Steady-State Stability is the ability of the *IESO-controlled grid* to remain in synchronism during relatively slow or normal load or generation changes and to damp out oscillations caused by such changes.

Damping Factor

The damping factor provides a measure of the steady-state stability margin of a power system. If an eigenvalue state-space model of the power system is available, then the damping factor (ξ) is:

$$\xi = \frac{-\delta}{\sqrt{\delta^2 + \omega^2}}$$

Where δ , and ω are the real and imaginary parts of the critical eigenvalue. If δ is negative, the oscillations will decay.

Where the eigenvalues are not available δ , and ω may be measured from time domain simulations by assuming that the oscillations are exponentially damped sinusoids in a second order system.

Operating Security Limits should ensure a damping factor equal to or greater than 0.03 under normal operating conditions.

B.3.2 POST-CONTINGENCY CRITERIA

TRANSIENT STABILITY CRITERIA

The transient stability performance of a power system is its ability to maintain synchronism between its parts when it is subjected to a loss of system element(s), usually accompanied by a fault.

The system model must meet the criteria listed below during the period of simulated real time, normally three to thirty seconds, following the most severe contingency set by the *IESO* policy with due regard to reclosure, generation rejection and/or load rejection.

Relay Margin

Following fault clearance or the loss of an element without a fault, the margin on all instantaneous and timed distance relays that affect the integrity of the *IESO-controlled grid*, including generator loss of excitation and out-of-step relaying at major generating stations, must be at least 20 and 10 percent, respectively.

The margin on all other relays whose operation would not affect the integrity of the *IESO-controlled Grid*, such as 115 kV or radial 230 kV circuit protections, generator loss of excitation and out-of-step protections on small generating units, those associated with transformer backup protections, must be at least 15 percent on all instantaneous relays and zero percent on all timed relays having a time delay setting less than or equal to 0.4 seconds.

For those relays having a time delay setting greater than 0.4 seconds, the apparent impedance may enter the timed tripping characteristic, provided that there is a margin of 50 percent on time. For example, the apparent impedance does not remain within the tripping characteristic for a period of time greater than one-half of the relay time delay setting.

The margin on all system relays, such as change of power relays, must be at least 10 percent.

Transient Stability Margin

The *IESO-controlled grid* must display a transient stability margin of at least 10 percent, calculated on the basis that the system must remain transiently stable if the most critical System Operating Parameter is increased to a value corresponding to a value at 10 percent higher than the Operating Security Limit.

The minimum Relay Margin Criteria should be satisfied at the appropriate Operating Security Limit.

System Dynamic Oscillations

The *IESO-controlled grid* must display damping of dynamic oscillations, if they exist. Acceptable damping is demonstrated by attenuation of the amplitude of the envelope of the oscillations for at least 10 to 20 seconds following the critical contingency.

Voltage Collapse/Stability

The *IESO-controlled grid* must display a voltage collapse/stability margin of at least 10 percent, calculated on the basis that the post-contingency voltage collapse will not occur if the most critical system operating parameter is increased to a value at 10 percent higher than the Operating Security Limit.

POST-CONTINGENCY STEADY STATE CRITERIA

Following the most severe operating contingency, the *IESO-control grid* must meet the following criteria in the steady-state prior to operator intervention, when operating at the Operating Security Limit.

Post-contingency Steady-State Stability

The computed Damping Factor should be equal to or greater than 0.01 for all modes.

Post-Contingency Voltage Levels

The post-contingency voltage levels on the *IESO-controlled grid* following the most critical single and double-element contingencies specified in section B.2 must be within 5 to 15 percent of their pre-contingency levels as specified below.

IESO-controlled Grid	IESO-controlled grid Condition	Contingency	Permissible Voltage Change in Percent	
			Before Tap Changer Action	After Tap Changer Action
NPCC Impactive	Normal	Single-element	5	10
		Double-element	10	15
	Emergency	Single-element	10	15
NPCC Non-Impactive And Local Areas	Normal	Single-element	10	15
	Emergency	Single-element	10	15

– End of Section –

Appendix C: SPS Restrictions During High Risk Operating State

Refer to Notes A and B

Contingency Type		<i>High Risk Operating State Due to Adverse Weather</i> (refer to notes C, D and E)	<i>High Risk Operating State Due to Conditions Other than Adverse Weather (E)</i>	
500 kV	Double Element Contingency	No restrictions to G/R or L/R		
	Single Element Contingency	G/R is permissible, provided: (a) its exposure is limited to outage periods or short-duration periods, or (b) its magnitude is reduced during adverse weather periods		
		Type I applications: L/R is permissible, provided <i>IESO-controlled grid</i> security criteria could not otherwise be satisfied.	Type III applications: L/R is permissible, provided <i>IESO-controlled grid</i> security criteria could not otherwise be satisfied.	Conditions that may lead to the declaration of a high risk operating state are specified in Section 4.2 of this document. Under these conditions: (1) The SPS must not be utilized if a fail-to-trip condition is suspected. (2) In all other situations, the primary concern is the impact of a false SPS operation, and the increased exposure to load rejection. The following restrictions therefore apply: <ul style="list-style-type: none"> • G/R or Generation Runback may be selected, but its use should be minimized or avoided where possible. • L/R may be selected, as follows: Type I applications: L/R is permissible, provided <i>IESO-controlled grid</i> security criteria could not otherwise be satisfied. Type III applications: L/R is permissible, provided <i>IESO-controlled grid</i> security criteria could not otherwise be satisfied.
230 kV	Double Element Contingency	No restrictions to G/R or L/R		
	Single Element Contingency	G/R is permissible, provided the only other alternative is to remove the unit from service, or the unit would be automatically removed from service as a result of the initiating contingency		
Type I applications: L/R is permissible, provided <i>IESO-controlled grid</i> security criteria could not otherwise be satisfied.		Type III applications: L/R is permissible, provided <i>IESO-controlled grid</i> security criteria could not otherwise be satisfied.		
115 kV	Double Element Contingency	Not observed		
	Single Element Contingency	G/R is permissible, provided the only other alternative is to remove the unit from service, or the unit would be automatically removed from service as a result of the initiating contingency,		
L/R is permissible, provided <i>IESO-controlled grid</i> security criteria could not otherwise be satisfied.				

(A) Conditions under which *high-risk operating state* may be declared are defined in Section 4.1. The restrictions in this table do not apply during an *emergency operating state*.

(B) *SPS* policy refers to normally recognized contingencies. An *SPS* may be selectively used to provide additional *security* beyond normal criteria, provided the above restrictions are satisfied.

(C) Weather conditions to be considered are those within the Weather Advisory Area, which is within 50 km of the circuits for which the *SPS* is selected.

(D) During extreme weather conditions, additional unrestricted *SPS* selections may be made per Note (B) to respect extreme contingencies.

(E) The Bruce SPS is limited to 2 unit arming and no load rejection is permitted. The load rejection portion of the scheme should be maintained only to overcome difficulties in the operating time frame that would otherwise require pre-contingency non-dispatchable load shedding.

– End of Section –

Appendix D: Load and Generation Rejection and Generation Runback Selection Criteria

In addition to the following, instances where more than one of the load rejection, generation rejection or generation runback scheme could be operated for a single contingency event should be minimized to the extent practical.

Load Rejection Selections

- a. For any specific contingency, the maximum amount of load rejection (L/R) cannot exceed 1000 MW.
- b. The load rejection portion of the Bruce Special Protection System shall not be used in conjunction with generation rejection to maintain Bruce stability. The load rejection portion of the scheme should be maintained only to overcome difficulties in the operating time frame that would otherwise require pre-contingency non-dispatchable load shedding.
- c. The use of L/R is permissible only if the affected *IESO-controlled grid Delivery Points* will remain within *reliability* performance standards.
- d. Where the selection of L/R is used to prevent the post-contingency thermal overloading of *IESO-controlled grid* components:
 - (ss) L/R may be selected whenever the post-contingency loading without such rejection would exceed the appropriate Limited Time Rating, in the amount sufficient to respect that rating.
 - (tt) If the lack of fast-acting control actions combined with the complexities of post-rejection operation, will jeopardize the ability to reach long-time ratings within the appropriate “limited” time, then rejection of sufficient load to prevent loading beyond the long-time ratings will be permitted.
- e. L/R should be selected to satisfy the following in order of priority:
 - (uu) **Security.** L/R selections must satisfy system *security* requirements for specific station and/or a specific megawatt requirement (to within an acceptable deadband). L/R must be selected such that the resulting transmission conditions do not prevent L/R actions to alleviate the system *security* concerns. L/R selections in the vicinity of a nature or man-made disaster must not hamper *emergency* measures.
 - (vv) **Trip History.** L/R selections should attempt to equalize the number of L/R operations for each station over the long term and minimize the exposure of any station to two successive Load Rejections.
 - (ww) **Minimize Number of Stations.** The number of stations selected for rejection should be minimized.
 - (xx) **Area Fairness.** Where L/R may be available for selection in more than one area, the stations selected for L/R should be distributed among each participating area.

This distribution should be in approximate proportion to the percentage of the total load supplied by all areas involved in the scheme.

Generation Rejection Selections

- a. Generation Rejection (G/R) should be selected to satisfy the following in order of priority:
 - (yy) **Security.** G/R requirements must satisfy system *security* requirements for specific unit selections and/or specific megawatt requirement (to within an acceptable deadband).
 - (zz) **Minimize Number of Units.** The number of units selected and total megawatts selected for G/R should be minimized within the constraints imposed by plant and system operating conditions.
 - (aaa) **Trip History.** Selections should attempt to equalize the number of unit trips based on history.
- b. Where the selection of G/R is used to prevent the post-contingency thermal overloading of *IESO-controlled grid* components:
 - (bbb) G/R may be selected whenever the post-contingency loading without such rejection would exceed the appropriate Limited Time Rating in the amount sufficient to respect that rating.
 - (ccc) If the lack of fast-acting control actions combined with the complexities of post-rejection operation, will jeopardize the ability to reach long-time ratings within the appropriate “limited” time, then rejection of sufficient generation to prevent loading beyond the long-time ratings will be permitted.
- c. Ideally, sufficient generation should be selected for rejection to observe operating *security limits* so that manual corrective measures can be avoided, following a G/R operation, when attempting to achieve a minimum level of *IESO-controlled grid security*.
- d. G/R selections should be made, to the extent practicable, to address any *market participant facility* concerns, such as:
 - (ddd) maximum number of units selected within a single *control center*;
 - (eee) the minimum number of unselected generating units; and
 - (fff) unavailability or preferences of specific units for G/R selection.
- e. The Brice SPS is limited to 2 unit arming and no load rejection is permitted.

Generation Runback Selections

All policies in place for G/R apply equally to Generation Runback.

– End of Section –

Appendix E: Emergency Operating State Control Actions

The following tables reflect the hierarchy of control actions available to the *IESO* leading up to and during an “*emergency operating state*”. Section E.1 addresses the actions initiated both in advance of the declaration of and during the *Emergency Operating State* where only the *IESO Control Area* is deficient. Section E.2 however addresses the scenario where the *IESO* and an external *control area* are both faced with generation deficiency.

While the tables provide the anticipated order of control actions, **the *IESO* may initiate control actions at any point in the hierarchy depending on the specific circumstances and conditions of the *IESO* or external *control area*.** In addition, the *IESO* may alter the order in which the control actions are implemented to respond to *reliability* concerns.

It should also be stressed that as a general principle the *IESO* will not take any control actions that do not provide a **net** benefit to the operating condition. Adherence to this principle may lead to scenarios where exports from congested regions within Ontario continue to flow while *non-dispatchable load* elsewhere in Ontario is being curtailed.

The *IESO* will not curtail linked wheeling transactions to support the overall adequacy of the *IESO* controlled grid. This curtailment would have no beneficial effect as both the injection and withdrawal would be simultaneously curtailed in accordance with NERC Standards. The *IESO* may however curtail a linked wheeling transaction where the transaction was contributing to transmission security concerns or overloads which are causing either global or local adequacy concerns.

Legend applied to the last 4 columns of the table, indicating the status of the *IESO-controlled grid* associated with each control action:

- A** 30-minute *operating reserve*, 10-minute *operating reserve* and *AGC* reserve maintained
- B** 10-minute *operating reserve* and *AGC* reserve maintained
- C** 10-minute synchronized *operating reserve* and *AGC* reserve maintained
- D** *AGC* reserve maintained

E.1 Actions in Advance of and During the IESO Controlled Grid Emergency Operating State

No.	Action	Description	References	A	B	C	D
-----	--------	-------------	------------	---	---	---	---

No.	Action	Description	References	A	B	C	D
1	Issue Weekly Security and Adequacy Assessment (SAA)	These assessments are published 15-34 days out and would identify any forecast capacity and/or <i>energy</i> deficiencies.	<i>Market Rules</i> – Chapter 5 sections 7.3.1.3 & 7.4.3 Market Manual Part 7.2 – Near-Term Assessments and Reports	Y			
2	Issue Daily Security and Adequacy Assessment (SAA)	This assessment comes 3-14 days out and would identify any forecast capacity and/or <i>energy</i> deficiencies.	<i>Market Rules</i> – Chapter 5 sections 7.3.1.4 & 7.4.4 Market Manual Part 7.2 – Near-Term Assessments and Reports	Y			
3	<i>Outage</i> Management Process – reject <i>outage</i> applications	This rejection applies only to those <i>outages</i> that have not received advance approval. Advance approval is received 2 <i>business days</i> prior to the start of an <i>outage</i> .	<i>Market Rules</i> – Chapter 5 section 6.4.4.1 Market Manual Part 7.3 - Outage Management	Y			
4	Issue System Advisory for undergeneration in System Status Report (SSR) Note: Where appropriate, the SSR may be issued after each control action.	This report is produced between 0-2 days in advance and would include the undergeneration advisory (report could be issued very close to real-time if needed). In this instance the advisory would indicate a lack of installed resources.	<i>Market Rules</i> – Chapter 7 section 12.1.3.2 Market Manual Part 7.2 – Near-Term Assessments and Reports	Y			
5	Issue Notification to (ELRP) Emergency Load Reduction Program Participants	The IESO will issue a request for specified Emergency Load Reduction Participants to submit Load reduction offers for a specified period. The <i>IESO</i> will normally issue this notification if it foresees a situation where activation of ELRP will be required to prevent/mitigate the following emergency control actions: <ul style="list-style-type: none"> • purchase of emergency energy, • implementation of environmental variances or • activation of a 3% or 5% voltage reduction 	Market Manual 10: Emergency Load Reduction Program <i>IESO</i> Internal Procedures	Y			
6	Issue General or	This is a public appeal for the	<i>IESO</i> internal procedures	Y			

No.	Action	Description	References	A	B	C	D
	Public Appeal	general populous to conserve <i>energy</i> and is usually a media based appeal. The <i>IESO</i> will normally issue an appeal only if the situation is expected to progress to the point that a 5% voltage reduction would also be expected to be activated.					
7	Issue System Advisory for undergeneration in System Status Report (SSR) Note: Where appropriate, the SSR may be issued after each control action.	This report is produced no more than 1 day in advance and would include the undergeneration advisory. The report could be issued very close to real-time if needed. In this case the advisory would indicate a lack of <i>offers</i> and <i>bids</i> .	<i>Market Rules</i> – Chapter 7 section 12.1.3.2 <i>Market Manual</i> Part 7.2 – Near-Term Assessments and Reports	Y			
8	<i>Outage</i> Management Process – revoke approved <i>outages</i>	Revoke impactful <i>outages</i> that have received advance approval (from 2 <i>business days</i> in advance of <i>outage</i> start up to real-time). This may trigger compensation of <i>generators</i> .	<i>Market Rules</i> - Chapter 5 sections 6.4.4.1 and 6.4.9 <i>Market Manual</i> Part 7.3 – <i>Outage</i> Management	Y			
9	Manage Inadvertent Payback	When inadvertent is owed by the <i>IESO</i> , the <i>IESO</i> may unilaterally or bilaterally payback the inadvertent. To the extent that this payback is contributing to the deficiency, such payback shall be discontinued. If the payback benefits the situation in the <i>IESO control area</i> , it will continue.	<i>IESO</i> internal procedures	Y			
10	Manage Time Error Correction	When time-error correction requires an over-generation of <i>IESO control area</i> resources, time-error correction shall be discontinued.	<i>IESO</i> internal procedures	Y			
11	<i>Outage</i> management process – recall <i>outages</i>	<i>Outages</i> that can be recalled in a timely fashion will be recalled. This may trigger compensation of <i>generators</i> .	<i>Market Rules</i> - Chapter 5 sections 6.4.4.1, 6.4.11 <i>Market Manual</i> Part 7.3 – <i>Outage</i> Management	Y			
12	Issue <i>NERC</i> Energy Emergency Alert 1 (EEA-1)	The <i>IESO control area</i> has (or expects to have) all available resources in use.	<i>NERC Reliability Standard</i> – EOP-002, Attachment 1	Y			

No.	Action	Description	References	A	B	C	D
13	Issue System Emergency Advisory in System Status Report (SSR) Note: Where appropriate, the SSR may be issued after each control action.	This SSR will be accompanied by a System Emergency Advisory indicating the <u>potential for the declaration</u> of an <i>emergency operating state</i> .	<i>Market Rules</i> - Chapter 7 section 12.1.3.3	Y			

No.	Action	Description	References	A	B	C	D
14	Constrain Dispatch of internal resources to alleviate current or future ramping issues	These control actions, where available and implemented, are intended to <u>avoid the declaration</u> of an <i>emergency operating state</i> . Daily Energy Limited Resources would only be constrained on at this point if other resources were not available.	<i>Market Rules</i> : Chapter 5 Sections 1.2.1 and 2.3.2 Chapter 7 Sections 7.2.1.1, 7.2.5.1 and 11.3.3	Y			
15	Discontinue Commissioning Tests	During the commissioning of a <i>generation unit</i> the <i>IESO</i> may be required to carry additional reserve due to the increased likelihood of unit failure. The <i>IESO</i> may request that all commissioning tests halt so that the reserve requirement is returned to normal levels.	<i>Market Rules</i> – Chapter 5 section 4.5.1.3	Y			
16	During the transaction checkout process, include remaining Exports, <u>as recallable</u> to maintain 30-minute <i>operating reserve</i> .	This pertains to those Exports that were not needed to be made recallable previously	<i>Market Rules</i> - Chapter 7, Appendix 7.5 <i>IESO Internal Procedures</i>	Y			
17	Include any 3% voltage reductions not already included through market mechanisms as 30-minute <i>operating reserve</i>	This action will help to maintain the 30-minute <i>operating reserve</i> and will only be included if all available offers for OR are utilized and exports have been identified as recallable for 30-minute reserve.	<i>Market Rules</i> – Chapter 5 section 10.3	Y			
18	The following 7 control actions can be used only if the 30-minute <i>operating reserve</i> shortfall is forecasted to last beyond 4 hours from the time the shortfall was first identified. Implement control actions 18b through 18g in a timely manner as to resolve the 30-minute shortfall prior to the end of the 4 hour period.						
18a	Issue <i>NERC Energy Emergency Alert 2 (EEA-2)</i>	The <i>IESO control area</i> has or is about to initiate load management procedures.	<i>NERC Reliability Standard</i> – EOP-002, Attachment 1	Y			
18b	Include remaining Exports that are flowing within the hour, <u>as recallable</u> to maintain 30-minute <i>operating reserve</i> .	Exports that are flowing within the hour will be allowed to flow and considered recallable. This pertains to those Exports flowing within the hour that were not needed to be made recallable previously	<i>Market Rules</i> - Chapter 7, Appendix 7.5 IESO Internal Procedures	Y			

No.	Action	Description	References	A	B	C	D
18c	Constrain Dispatch of Resources	These control actions, where available and implemented, are intended to <u>avoid the declaration</u> of an <i>emergency operating state</i> . Use of Daily Energy Limited resources, constraining on imports and off exports may be used at this point.	<i>Market Rules</i> : Chapter 5 Sections 1.2.1 and 2.3.2 Chapter 7 Sections 7.2.1.1, 7.2.5.1 and 11.3.3	Y			
18d	Include 5% voltage reductions as 30-minute <i>operating reserve</i> if not already included through market mechanisms as 30-minute <i>operating reserve</i> .	This action will help to maintain the 30-minute <i>operating reserve</i> requirement	<i>Market Rules</i> – Chapter 5 section 10.3	Y			
18e	Issue System Emergency Advisory in System Status Report (SSR) Note: Where appropriate, the SSR may be issued after each control action.	This SSR will be accompanied by a System Emergency Advisory that will include the <u>declaration</u> of the <i>emergency operating state</i> .	<i>Market Rules</i> – Chapter 7 section 12.1.3.3	Y			
18f	Activate Emergency Load Reduction Program (ELRP)	The IESO will issue a request for specified Emergency Load Reduction Participants to reduce load for a specified period. The <i>IESO</i> will normally issue this activation, if it has not already done so, to prevent the purchase of emergency energy, the need to implement environmental variances or the need to activate a 3% or 5% voltage reduction.	Market Manual 10: Emergency Load Reduction Program <i>IESO</i> Internal Procedures	Y			
18g	Purchase <i>emergency energy</i> and request <i>emergency assistance</i>	Purchase resources not made available through market mechanisms to eliminate the deficiency. These purchases are made to maintain 30-minute <i>operating reserve</i> and are not providing support to the exports that may be flowing at the time. The source of the purchases must be the seller's surplus <i>energy</i> .	Market Rules - Chapter 5 Section 2.3.3A	Y			
The <i>IESO</i> is now no longer able to operate to respect the 30-minute <i>operating reserve</i> requirement. The preceding control actions are insufficient to meet the full 30-minute reserve requirement.							

No.	Action	Description	References	A	B	C	D
19	Include remaining Exports, as <u>recallable</u> for 10-minute non-synchronized reserve.	Exports will be made recallable for 10-minute non-synchronized <i>operating reserve</i> activation during the transaction checkout process or earlier as required to maintain the 90/105 minute <i>operating reserve</i> requirement.	<i>Market Rules</i> - Chapter 7, Appendix 7.5		Y		
20	Constrain Dispatch of Resources including Daily Energy Limited resources and imports	These control actions, where available and implemented, are intended to <u>avoid the declaration</u> of an <i>emergency operating state</i> .	<i>Market Rules</i> : Chapter 5 Sections 1.2.1 and 2.3.2 Chapter 7 Sections 7.2.1.1, 7.2.5.1 and 11.3.3		Y		
21	Give advance warning to the Ministry of the Environment Spills Action Centre (by phone 1-800-268-6060) and the Ministry of Natural Resources (1-800-656-8626) of potential for Environmental Variance request from <i>market participants</i> and issue SSR.	This will allow MOE and MNR time to alert their Regional Offices and be prepared to approve Environmental Variance Requests. The IESO will only provide this notification if the situation is expected to progress to the point environment variance requests will be required. The IESO will issue a SSR.	<i>IESO</i> internal procedures		Y		
22	Include any 3% voltage reductions not already included through market mechanisms as 10-minute <i>operating reserve</i> .	This action will help to maintain the 10-minute <i>operating reserve</i> and will only be utilized if all exports have been identified as recallable for 10-minute reserve.	<i>Market Rules</i> – Chapter 5 section 10.3		Y		
23	Issue <i>NERC</i> Energy Emergency Alert 2 (EEA-2)	The <i>IESO control area</i> has or is about to initiate load management procedures.	<i>NERC Reliability Standard</i> – EOP-002, Attachment 1		Y		
24	Include any 5% voltage reductions as 10-minute <i>operating reserve</i> not already included through market	This action will help to maintain the 10-minute <i>operating reserve</i> and will only be utilized if all exports identified as recallable and 3% voltage reduction are insufficient to maintain the 10-	<i>Market Rules</i> – Chapter 5 section 10.3		Y		

No.	Action	Description	References	A	B	C	D
	mechanisms as 10-minute <i>operating reserve</i> .	minute non-synchronized requirement.					
25	Issue System Emergency Advisory in System Status Report (SSR) Note: Where appropriate, the SSR may be issued after each control action.	This SSR will be accompanied by a System Emergency Advisory that will include the <u>declaration</u> of the <i>emergency operating state</i> .	<i>Market Rules</i> – Chapter 7 section 12.1.3.3		Y		
26	Activate Emergency Load Reduction Program (ELRP)	The IESO will issue a request for specified Emergency Load Reduction Participants to reduce load for a specified period. The <i>IESO</i> will normally issue this activation, if it has not already done so, to prevent the purchase of emergency energy, the need to implement environmental variances or the need to activate a 3% or 5% voltage reduction.	Market Manual 10: Emergency Load Reduction Program <i>IESO</i> Internal Procedures		Y		
27	Request <i>market participants</i> to seek prior approval of environmental variances and issue SSR.	The <i>IESO</i> will request <i>market participants</i> to seek prior approval for environmental variances. The environmental variances will be utilized only if implementing 3% voltage reduction. The IESO will issue a SSR.	<i>IESO</i> internal procedures		Y		
28	Purchase <i>emergency energy</i> and request <i>emergency assistance</i>	Purchase resources not made available through market mechanisms. These purchases are made to maintain 10-minute <i>operating reserve</i> and are not providing support to the exports that may be flowing at the time. The source of the purchases should be the seller's surplus <i>energy</i> or 30 minute reserve.	<i>Market Rules</i> – Chapter 5 section 2.3.3A		Y		
<p>The <i>IESO</i> is no longer operating to respect the 10-minute non-synchronized <i>operating reserve</i> requirement and has only enough resources available to meet the 10-minute synchronized reserve and minimum <i>automatic generation control</i> (AGC) requirements. The preceding control actions are insufficient to maintain 10-minute non-synchronized reserve.</p>							
29	Exports identified as recallable for 10-	Exports that bid MMCP (or are flowing within the hour) will not	<i>IESO</i> internal procedures			Y	

No.	Action	Description	References	A	B	C	D
	minute non-synchronized reserve are recalled. Note: Should the recall of an identified export cause a jurisdiction to enter into (or aggravate a jurisdiction in) the <i>emergency operating state</i> the <i>IESO</i> will, in accordance <i>good utility practice</i> , take additional steps to support the dependent jurisdiction on a reciprocal step by step basis. This support is described in section E.2.	be scheduled (or are recalled) to maintain 10-minute synchronized <i>operating reserve</i> . Note: There will be no exports flowing prior to implementing the next control action.					
30	Activate Emergency Load Reduction Program (ELRP)	The <i>IESO</i> will issue a request for specified Emergency Load Reduction Participants to reduce load for a specified period. The <i>IESO</i> will normally issue this activation, if it has not already done so, to prevent the purchase of emergency energy, the need to implement environmental variances or the need to activate a 3% or 5% voltage reduction.	Market Manual 10: Emergency Load Reduction Program <i>IESO</i> Internal Procedures			Y	
31	Give warning to the Ministry of the Environment Spills Action Centre (by phone 1-800-268-6060) that the <i>IESO</i> is about to request <i>market participants</i> to implement their environmental variances.	This will allow MOE to alert their Regional Offices that the <i>market participants</i> is about to be requested by the <i>IESO</i> to implement their coal, nuclear, and gas environmental variances.	<i>IESO</i> internal procedures				
32	Implement MOE environmental variances and issue SSR.	The <i>IESO</i> will request <i>market participants</i> to implement available MOE environmental variances to allow thermal generators (coal, nuclear, gas) to increase their output and subsequently issue a SSR.	<i>IESO</i> internal procedures			Y	
33	Implement 3% voltage reductions	The <i>IESO</i> has reduced voltage by 3% at the distribution level. Power quality affected but no “real” load cut.	<i>Market Rules</i> – Chapter 5 section 10.3			Y	

No.	Action	Description	References	A	B	C	D
34	Disregard High-Risk Limits	This action will allow the <i>IESO</i> to make additional bottled <i>energy</i> available at the expense of increased risk to system <i>security</i> .	<i>IESO</i> internal procedures			Y	
35	Purchase <i>emergency energy</i> and request <i>emergency assistance</i>	Purchase resources not made available through market mechanisms. The source of the purchases should be the seller's surplus <i>energy</i> or 30-minute reserve made available by Step 29: Disregard High Risk Limits.	<i>Market Rules</i> – Chapter 5 section 2.3.3A			Y	
The <i>IESO</i> is no longer operating to respect the 10-minute synchronized <i>operating reserve</i> requirement and has only enough resources available to meet the minimum <i>automatic generation control (AGC)</i> requirements.							
36	Activate Emergency Load Reduction Program (ELRP)	The <i>IESO</i> will issue a request for specified Emergency Load Reduction Participants to reduce load for a specified period. The <i>IESO</i> will normally issue this activation, if it has not already done so, to prevent the purchase of emergency energy, the need to implement final environmental variances or the need to activate 5% voltage reduction.	Market Manual 10: Emergency Load Reduction Program <i>IESO</i> Internal Procedures				Y
37	Implement 5% voltage reductions	The <i>IESO</i> has reduced voltage by 5% at the distribution level. Power quality affected but no “real” load cut. Expect significant customer complaints and requests for <i>exemption</i> .	<i>Market Rules</i> – Chapter 5 section 10.3				Y
38	Give warning to the Ministry of Natural Resources (1-800-656-8626) that the <i>IESO</i> is about to request <i>market participants</i> to implement environmental variances	This will allow MNR to alert their Regional Offices that the <i>market participants</i> is about to be requested by the <i>IESO</i> to implement their hydroelectric environmental variances.	<i>IESO</i> internal procedures				Y
39	Implement all remaining approved environmental variances and issue SSR.	The <i>IESO</i> will request <i>market participants</i> to implement all remaining approved environmental variances and subsequently issue a SSR.	<i>IESO</i> internal procedures				Y

No.	Action	Description	References	A	B	C	D
40	Issue <i>NERC</i> Energy Emergency Alert 3 (EEA-3)	This publishes to all that “Firm Load interruption is imminent or in process”. These alerts are posted on the <i>NERC</i> public web-site.	<i>NERC Reliability Standard</i> – EOP-002, Attachment 1				Y
41	Operate to Emergency Condition Limits	This action will allow the <i>IESO</i> to make additional bottled <i>energy</i> available at the expense of increased risk to system <i>security</i> .	<i>IESO</i> internal procedures				Y
42	Purchase <i>emergency energy</i> and request <i>emergency</i> assistance	Purchase resources not made available through market mechanisms. The source of the purchases should be the seller’s surplus <i>energy</i> or <i>operating reserve</i> including 10-minute reserve made available by Step 34: Operate to Emergency Condition Limits.	<i>Market Rules</i> – Chapter 5 section 2.3.3A				Y
43	Implement Emergency Demand Response Program (EDRP)	EDRP is a <i>reliability</i> -based program intended to mitigate the adverse impacts of shortages when all commercial mechanisms in the market have been exhausted.	<i>Market Rules</i> – Chapter 5 section 4.8A				Y
44	Curtail <i>non-dispatchable load</i>	Curtailement achieved through <i>emergency</i> block or rotational load shedding.	<i>Market Rules</i> – Chapter 5 section 10.3				Y

E.2 Emergency Operating State Actions (IESO and External Control Area Deficiency)

Legend applied to the last 4 columns of the table, indicating the status of the *IESO-controlled grid* associated with each control action:

- A** 30-minute *operating reserve*, 10-minute *operating reserve* and *AGC* reserve maintained
- B** 10-minute *operating reserve* and *AGC* reserve maintained
- C** 10-minute synchronized *operating reserve* and *AGC* reserve maintained
- D** *AGC* reserve maintained

No.	Action	Description	References	A	B	C	D
<u>Initial actions</u>							
The IESO will:							
<ul style="list-style-type: none"> Utilize all dispatchable resources including Ontario dispatchable load/generation, bid at +MMCP to satisfy demand and reserve requirements. Provide notices of expected supply shortfall, reject, revoke and recall outages, cancel commissioning test and take all other acceptable control actions as articulated in the section E.1 to minimize the deficiency. Include exports identified as recallable for <i>operating reserve</i> (30-minute and 10-minute non-synchronized) and voltage reduction as sources of <i>operating reserve</i> 							
<i>At this point all remaining exports would be supplying non-dispatchable load in the deficient jurisdiction and it would be in a state comparable to the Ontario “Emergency Operating State”. The following actions will be taken as long as the deficient area remains in a comparable or more severe state:</i>							
1	Curtail exports to jurisdictions not purchasing <i>emergency energy</i> or taking equivalent action.		<i>Market Rules</i> – Chapter 5 section 2.3 <i>IESO</i> internal procedures			Y	
2	Purchase Emergency Energy and request <i>emergency</i> assistance.	Purchase resources not made available through market mechanisms.	<i>Market Rules</i> – Chapter 5 section 2.3.3A			Y	
3	Curtail exports to jurisdictions not implementing 3% voltage reduction or taking equivalent action.		<i>Market Rules</i> – Chapter 5 section 2.3 <i>IESO</i> internal procedures			Y	
4	Implement 3% voltage reductions in Ontario.	The <i>IESO</i> has reduced voltage by 3% at the distribution level. Power quality affected but no “real” load cut.	<i>Market Rules</i> – Chapter 5 section 10.3			Y	

No.	Action	Description	References	A	B	C	D
5	Curtailed exports to jurisdictions not implementing 5% voltage reduction or taking equivalent action.		<i>Market Rules</i> – Chapter 5 section 2.3 <i>IESO</i> internal procedures			Y	
6	Implement 5% voltage reductions in Ontario.	The <i>IESO</i> has reduced voltage by 5% at the distribution level. Power quality affected but no “real” load cut. Expect significant customer complaints and requests for exemption.	<i>Market Rules</i> – Chapter 5 section 10.3				Y
7	Curtailed exports to jurisdictions not operating to <i>emergency</i> condition limits (or disregarding high-risk limits).		<i>Market Rules</i> – Chapter 5 section 2.3 <i>IESO</i> internal procedures				Y
8	Operate to <i>emergency</i> condition limits (or disregard high risk) in Ontario.		<i>IESO</i> internal procedures				Y
9	Curtailed remaining exports.		<i>Market Rules</i> – Chapter 5 section 2.3				Y
10	Implement Emergency Demand Response Program (EDRP)	EDRP is a reliability-based program intended to mitigate the adverse impacts of shortages when all commercial mechanisms in the market have been exhausted.	<i>Market Rules</i> – Chapter 5 section 4.8A				Y
11	Curtailed Ontario non-dispatchable loads.	Curtailed achieved through <i>emergency</i> block or rotational load shedding.	<i>Market Rules</i> – Chapter 5 section 10.3				Y

– End of Section –

References

Document ID	Document Title
MDP_RUL_0002	Market Rules for the Ontario Electricity Market
MDP_PRO_0024	Market Manual 2: Market Administration, Part 2.8: 10-Year Outlook and Related Information Requirements
IMP_MAN_0012	Market Manual 7: System Operations, Part 7.0: Systems Operations Overview
IMP_GOT_0002	Market Manual 7: System Operations, Part 7.6: Glossary of Standard Operating Terms
MDP_PRO_0040	Market Manual 7: Systems Operations, Part 7.1: Systems Operating Procedure
MDP_PRO_0016	Market Manual 1: Market Entry, Maintenance & Exit, Part 1.2: Facility Registration, Maintenance and De-registration
IMO_PRO_0033	Market Manual 7: System Operations, Part 7.9: Reliability Compliance Program
IMP_PRO_0033	Market Manual 7: System Operations, Part 7.2: Near-Term Assessments and Reports

– End of Document –